

TESTAVIT SCHUKI 1 LCD

Socket outlet testers

Using the new Testavit Schuki 1 LCD and 3 LCD, specialists easily check to see if sockets, cable drums or connecting cables are correctly connected in 230 V installations. Due to three LEDs, the connection status can be quickly and clearly determined. In addition, through the finger contact, it can be tested to see whether an impermissible, high contact voltage is applied at the protective earth connection. In addition, using the Testavit Schuki 1 LCD, a 30 mA FI circuit breaker (RCD) can be triggered via a pushbutton.

How you benefit:

- | Quick and safe checking of installations
- | Finger contact to check the protective earth connection
- | FI test (Schuki 1 LCD)
- | FI test (30 mA @ 230 V AC)

Specifications

Technical Data	TESTAVIT SCHUKI 1 LCD
Display	Optical, LCD and LED
Operating Voltage	230 V, 50 Hz
RCD Triggering	Yes (using test button)
Error Current	30 mA @ 230 V AC
Protection	IP 40
Overload Category	CAT II 300 V
Standard	IEC/EN 61010-1 (DIN VDE 0411)
Operating temperature	0–50 °C
Dimension	60 x 60 mm
Weight	54 g
Scope of Delivery	incl. operating instructions

