



- external antenna as required accessory of the repeater of the RP-NA16-KA series (control cabinet, fuse box)
- for extending the range with protection class 1 distributors and shielded electrical installation or disturbed reception
- building biology wireless technology according to enOcean standard
- with magnetic base for easy mounting
- The ANT-NA16 antenna is required for connection to the RP-NA16-KA repeater to increase the range and to improve any disturbed reception.
- The RP-NA16-KA repeater is installed in a switch cabinet (fuse box). This antenna is screwed onto the module and led out of the box. This ensures a clean function even in shielded electrical installations.
- The antenna is mounted outside the box with the help of an integrated magnetic base, which is either attached to the cabinet door or to a metal body disc (metal plate, etc.) that is screwed on, for example.

Order-No.: 721090
Short-Desc.: ANT-NA16

Accessories demand switches

ANT-NA16 (Antenna)

Technical data

height:	100 mm
height angled:	78 mm
colour:	black
weight:	ca. 60 g
switching range:	> 30 metre
cable length:	250 cm
antenna connection:	SMA 1.2-1.6
mounting:	magnetic base on outer door

Scope of delivery

antenna (1 pcs.)

instruction manual

Accessories needed

Repeater - RP-NA16-KA

